

1250 W VHF/FM Transmitter T3274



Highlights of the VHF/FM Transmitter T3274

- Simple and intuitive menu control via graphic display
- Service friendly design with plug-in Eurocard modules
- 19" slide-in technology of height 9 U
- All important functions and status information of the transmitter are simultaneously shown on the graphic display
- Prepared for all reserve concepts
- Directly modulated synthesizer with 10 kHz channel separation
- Integrated stereo encoder with deviation limiter
- Proven MOSFET technology of the power transistors
- Excellent reliability due to low junction temperatures of < 90° C at T (ambient) = 25° C
- Very good quality data in with respect to unweighted- and weighted S/N ratio, stereo cross-talk, frequency response and non-linear distortion
- Protective circuits against overvoltage, fan failure, overtemperature and mismatch
- RF output power continuously adjustable between 250 W and 1250 W in 1 W steps
- Each 250 W amplifier is equipped with a harmonic filter
- The output is delivered by five 250 W amplifiers, connected in parallel by an external 5:1 combiner.

Technical Data

RF output connector
 Remote interfaces

Operating mode (freely selectable)
 Number of preset frequencies
 AF patch-plug for the left- and right channel
 Level controller for 40 kHz deviation
 Setting accuracy
 Pilot tone level adjustable
 RDS input level adjustable
 SCA input level adjustable
 Preemphasis (on/off switchable)
 Cooling
 Operational in the temperature range
 Humidity
 Dimensions W x H x D in mm
 Weight

7/16, 50 Ω
 Standard: RS232
 Option: Relay, BITBUS, SNMP or HTTP
 Mono, stereo, MPX, (L+R)/2
 6
 Option, LEMO-Triaial
 - 5.25 dBm ... + 12.5 dBm, in 0.25 dB steps
 ≤ 0.1 dB
 - 25 dBu ... - 5 dBu
 - 23 dBu ... - 9.5 dBu
 - 23 dBu ... - 9.5 dBu
 25, 50, 75 μsec
 Internal fan
 - 10° C ... + 50° C
 to 95 %, without dew
 483 x 396 x 370
 35 kg

The VHF/FM transmitter fulfils the national standards as well as the technical specifications of the ARD (5/ 3.1), the Deutschen Telekom (TS 0216) and ETSI EN 302 018-2.

Transmitter Power

Output power P_{RF}	1250 W
Amplifiers	5 * 250 W
Output power setting range	250 W ... 1250 W, continuous
Full power up to VSWR = 1.5	thereafter down regulation of output power

Frequency

Frequency range	87.5 MHz ... 108 MHz, in 10 kHz steps
Frequency change	< 1 sec
Frequency drift over 3 months	< 300 Hz
Setting accuracy	< 50 Hz
Middle frequency shift during modulation	0 Hz
Deviation instability	< 1 %
Warm-up time	< 5 min

Out-of-band Emission

0.2 MHz	< - 110 dBc/Hz
0.3 MHz	< - 126 dBc/Hz

Spurious Emission

Harmonic emissions	< - 80 dBc
Noise power density	< - 150 dBc/Hz

Reverse Intermodulation Products

	> 15 dB
	> 2000 Ω or 600 Ω

Input Impedance**Linear Distortion**

Stereo cross-talk attenuation	
40 Hz ... 15 kHz	> 45 dB
Amplitude deviation	
40 Hz ... 65 kHz	\pm 0.1 dB
> 65 kHz ... 76 kHz	\pm 0.2 dB
100 kHz	- 2 dB \pm 0.5 dB
Damping of the 15 kHz low-pass	
40 Hz ... 15 kHz	< 0.2 dB
at 19 kHz	> 50 dB

Non-Linear Distortion

Distortion factor 40 Hz ... 15 kHz, at 75 kHz deviation	< 0.1 % = - 60 dB
---	-------------------

Selective S/N Ratio

Mono	> 80 dB
Stereo	> 80 dB

Unweighted S/N Ratio (effective peak value)

Mono	> 72 dB
Stereo	> 72 dB
AM unweighted S/N ratio, asynchronous	> 60 dB
AM unweighted S/N ratio, synchronous	> 60 dB

Weighted S/N Ratio (effective peak value)

Mono	> 70 dB
Stereo	> 70 dB
AM weighted S/N ratio, asynchronous	> 60 dB

Power Supply

Voltage range	1/N/PE 115 V	95 V ... 132 V
	1/N/PE 230 V	195 V ... 264 V
Mains frequency		47 Hz ... 63 Hz
Power consumption		2750 W at $P_{RF} = 1250$ W
$\cos \varphi$		> 0.7
Ready after mains failure		< 2 sec

Contact address:

TRANSRADIO SenderSysteme Berlin AG
 Mertensstr. 63,
 13587 Berlin, Germany
 Telephone: ++49-30-339 78-0
 Telefax: ++49-30-339 78-599
 Email: info@tsb-ag.de
 Internet: <http://www.transradio.de>